

**Part No. WFIL-N1737.5-1742.5F**

**1740MHz +/-2.5MHz Notch Filter/SMA**



**Features:**

- Low VSWR
- Low Insertion Loss
- High Performance



Electrical Specification	
Pass band	1200-1727.5 MHz 1752.5-2600 MHz
Description	Notch Filter
Center Frequency	1740 MHz
Insertion Loss	1.5dB max
Ripple	1.0dB max
Notch Depth	Fo ±2.5MHz:>60dB
V.S.W.R	1.5:1 max
Power Handling	2W CW
Impedance	50 Ohm
Connector Type	SMA
Dimension	169mm x 100mm x 53mm

Test Report

